

telpho10 Installation

Voraussetzungen:

- PC mit Intel oder VIA CPU
- Festplatte mit SATA Schnittstelle. Mindestens 2 GByte
- Netzwerkkarte

Booten Sie von der telpho10 Installations CD.

Achtung: Bei der Installation wird die vorhandene Festplatte gelöscht.

```
Creation date: Thu Apr  8 16:57:27 CEST 2010
These disks were generated on the following system:-
    Debian GNU/Linux 5.0 telpho
    Kernel 2.6.26-2-686 on a i686

To format and restore all files automatically, type 'nuke' <enter>.
To restore some/all files interactively, type 'interactive' <enter>.
To compare the archives with your filesystem, type 'compare' <enter>.
To boot to a command-line prompt (expert mode), type 'expert' <enter>.
You may add one or more of the following parameters as well:-

oondont eject - mondorestore will not eject the CD; this is useful if, for
oo             instance, your PC's case has a concealed CD-ROM drive
oonoresize   - your mountlist will not be adjusted to use your unallocated
oo             hard disk space
ootextonly   - do not call any Newt library routines; this is unattractive
oo             but valuable if you find your Newt library has bugs in it

e.g. Type 'nuke dont eject textonly' if you have an unstable Newt library and
a PC whose CD-ROM drive tray would be damaged if it unexpectedly ejected.

boot: _
```

Nach dem Bootvorgang erscheint der Eingabeprompt. Geben Sie „nuke“ ein und bestätigen Sie mit ENTER.

Die Installation beginnt automatisch.

```

WELCOME TO MONDO RESCUE
Restoring Automatically

Partitioning hard disks Done.
Formatting partitions Done.
Mounting devices Done.
Restoring OS and
Restoring from a backup Done.
Running GRUB... Done.
Unmounting devices Done.
Using tune2fs to
recheck filesystems Done.

Please wait. This may take a while.
Formatting /dev/sda1 OK
All partitions were unmounted OK
Restoring from CD-ROM OK
Your boot loader ran OK
All partitions were unmounted OK.
Mondo has restored your system.

Alert
Mondo has restored your system.
Please wait for the command prompt. Then remove the backup media and reboot.
Please visit our website at
http://www.mondorescue.org for more information.

OK
  
```

Nach erfolgreicher Installation bestätigen Sie mit „OK“.

```

Unmounting devices Done.
Using tune2fs to identify your ext2,3 partitions Done.
Run complete. Please remove media and reboot.
Mounting devices Done.
Unmounting devices Done.

Running post-nuke...sh: cannot create //Mondo.tmp.MJho8g/mondo-run-prog-thing.tmp: Directory nonexistent OK.
All partitions were unmounted OK.
sh: cannot create //Mondo.tmp.MJho8g/mondo-run-prog-thing.tmp: Directory nonexistent
Restore log (/var/log/mondorest.log) copied to /var/log on your hard disk
Mondo-restore is exiting (retval=0)
Execution run ended; result=0
Type 'less /var/log/mondorest.log' to see the output log
Type 'exit' to reboot the PC

BusyBox v1.2.1 (2008.12.01-10:22+0000) Built-in shell (ash)
Enter 'help' for a list of built-in commands.

sh: can't access tty; job control turned off
#
  
```

Geben Sie den Befehl „reboot“ ein und bestätigen Sie mit ENTER.

Weitere Informationen zur Inbetriebnahme und Konfiguration finden im aktuellen Handbuch.